

HYDROGEN GENERATING APPARATUS AND COMPONENTS THEREFOR

FIELD OF THE INVENTION

The present invention is directed to a hydrogen generating apparatus and in particular a hydrogen generating apparatus for use in motor vehicles to increase the performance of the engine of the motor vehicle.

BACKGROUND OF THE INVENTION

The use of hydrogen as a supplemental fuel in motor vehicle engines has been proposed to increase the performance of the engine. Hydrogen and oxygen, when used as part of the air/fuel mixture for the operation of the engine, have been found to increase the performance of the engine by increasing the mileage and by reducing the amount of emissions from the engine. The hydrogen and oxygen may be generated through electrolysis of an aqueous solution with the gases given off being mixed with the fuel and air supplied to the engine.

The generation of small quantities of hydrogen and oxygen using one or more electrolysis cells with the hydrogen and oxygen generated then being combined with the usual air/fuel mixture to improve the efficiency of internal combustion engines has been proposed in a number of prior patents. Some systems of these prior patents utilized the alternator or an auxiliary generator attached to the engine to provide the electrical power for the system.

One example of such a system is shown in U.S. Patent No. 4,271,793. This patent describes an internal combustion engine having a fuel system for feeding an air/fuel mixture to the combustion chamber and an electrical generation system, such as an alternator. An electrolysis cell was attached adjacent to the

engine to generate hydrogen and oxygen upon the application of a voltage between the cathode and the anode of the electrolysis cell. A gas delivery connects the cell to the engine fuel system for feeding the hydrogen and oxygen to the engine combustion chambers. The electrolysis cell was placed under a predetermined pressure to prevent the electrolyte from boiling off. The cell also included a cooling system and other safety features.

Another electrolysis cell is disclosed in U.S. Patent No. 5,231,954. The electrolysis cell of this patent was used for generating hydrogen and oxygen gases which were added to the fuel delivery system as a supplement to the gasoline or other hydrocarbons burned therein. The cell was designed to reduce the hazard of explosion by withdrawing the gases through a connection with the vacuum line of the positive crankcase ventilation (PCV) system of the engine and by utilizing a slip-fitted top cap for the electrolysis cell.

A further example of an electrolysis cell for use in connection with an internal combustion engine, for generating hydrogen and oxygen gases is shown in U.S. Patent No. 5,458,095. This system utilized an electric pump to draw the hydrogen and oxygen gases out of the cell, where the outlet side of the pump was connected to the air intake manifold using a hose having a terminating insert. The insert was formed from copper tubing bent at an appropriate angle to insure that the hydrogen and oxygen gas outlet from the pump was in the same direction as the downstream airflow in the air intake manifold.

Although much work has been conducted to advance automotive electrolysis systems, these systems have not been generally accepted due to safety and convenience concerns. A hydrogen generating system is required which overcomes at least some of the safety and convenience problems of previous systems.

SUMMARY OF THE INVENTION

The present invention is directed to a hydrogen generating system for use in internal combustion engines for increasing the efficiency of the engine and decreasing emissions from the engine. The hydrogen generating system of the present invention comprises an electrolysis cell for generating hydrogen and oxygen gases by electrolysis of an aqueous solution, a power source for providing electrical power to the electrolysis cell and an outlet flow means for introducing the generated gases into the intake manifold system of an internal combustion engine.

In accordance with one aspect of the present invention there is provided a hydrogen generating system for use in an internal combustion engine for increasing the efficiency of the engine and decreasing emissions from the engine, the hydrogen generating system comprising: an electrolysis cell for generating hydrogen and oxygen gases by electrolysis of an aqueous solution, a power source for providing electrical power to the electrolysis cell; an outlet flow means for introducing the generated gases into the intake manifold system of an internal combustion engine; a monitoring means for monitoring the operating conditions of the hydrogen generating system, the monitoring means including an electrolyte level monitoring device in the electrolysis cell including a tube, a circuit disposed in the tube, the circuit including a switch positioned adjacent a selected level of the aqueous solution and a float selected to float on the aqueous solution, the float being slidably engaged on the tube, and free to ride along the tube as driven by changes in the surface level of the aqueous solution and the float including means for actuating the switch as it rides along the tube; and a control means in communication with the monitoring means and adapted to control the operation of the hydrogen generating system in

response to the monitoring means, the control means including means in communication with the electrolyte level monitoring device and adapted to indicate when the level of the aqueous solution reaches the selected level as indicated by the float actuating the switch.

In one embodiment the switch is a reed switch disposed within the tube. There can be any number of switches in the circuit, preferably there are one or two switches. A magnet can be disposed in the float to act as the means for actuating the switch. In one embodiment, the control means lights an indicator light close to the cell to indicate when the liquid level rises to an upper acceptable level. In a preferred embodiment, the circuit enters the cell through an opening in the cell which is positioned above the normal upper level of the fluid.

In accordance with another aspect of the present invention, there is provided a hydrogen generating system for use in an internal combustion engine for increasing the efficiency of the engine and decreasing emissions from the engine, the hydrogen generating system comprising: an electrolysis cell for generating hydrogen and oxygen gases by electrolysis of an aqueous solution contained within the cell, the electrolysis cell having an outer surface; a power source for providing electrical power to the electrolysis cell; an outlet flow means for introducing the generated gases into the intake manifold system of an internal combustion engine; a monitoring means for monitoring the operating conditions of the hydrogen generating system, the monitoring means including an electrolyte level monitoring device including a tank circuit having an inductor and a capacitor connected in parallel, the inductor being an electrical wire wrapped at least one turn about the electrolysis cell adjacent a selected level of the aqueous solution within the electrolysis

cell, and interface circuitry for exciting the tank circuit such that a sine wave is generated and observing evidence of energy loss in the circuit; and a control means in communication with the monitoring means and adapted to control the operation of the hydrogen generating system in response to the monitoring means, the control means including means in communication with the electrolyte level monitoring device and adapted to indicate when the level of the aqueous solution reaches the selected level as indicated by the energy loss in the circuit.

Preferably, the circuit is disposed about the outer surface of the electrolysis cell so that no opening through the cell housing need be made. This avoids creating an opening susceptible to leakage. In one embodiment, there is an upper tank circuit and a lower tank circuit, indicating an upper electrolyte level and a lower electrolyte level respectively. The control means can be adapted to indicate level of electrolyte solution reaches the selected level by shutting down operation of the system, by sounding an alarm, by sending a message to a user display or by illumination of a light.

In accordance with another aspect of the present invention, there is provided a hydrogen generating system for use in an internal combustion engine of a vehicle for increasing the efficiency of the engine and decreasing emissions from the engine, the hydrogen generating system comprising: an electrolysis cell for generating hydrogen and oxygen gases by electrolysis of an aqueous solution; a power source for providing electrical power to the electrolysis cell as supplied by a battery power supply; an outlet flow means for introducing the generated gases into the intake manifold system of the internal combustion engine; a monitoring means for monitoring the operating conditions of the hydrogen generating system, the

monitoring means including a sensor for monitoring battery voltage; and a control means in communication with the monitoring means and adapted to control the operation of the hydrogen generating system in response to the monitoring means, the control means including means for comparing the battery voltage to a voltage indicative of proper alternator operation and controlling operation of the hydrogen generating system when the battery voltage is not indicative of proper alternator operation.

In one embodiment, the control means is further adapted to indicate that the battery voltage is not indicative of proper alternator operation.

In accordance with another aspect of the present invention, there is provided a hydrogen generating system for use in an internal combustion engine of a vehicle for increasing the efficiency of the engine and decreasing emissions from the engine, the hydrogen generating system comprising: at least one electrolysis cell for generating hydrogen and oxygen gases by electrolysis of an aqueous solution; a power source for providing electrical power to the electrolysis cell; an outlet flow means for introducing the generated gases into the intake manifold system of an internal combustion engine, the outlet flow means including a vacuum pump for drawing the generated gases under vacuum toward the internal combustion engine, the vacuum pump having an inlet tubing and an outlet tubing and a vacuum control arrangement for conveying supplemental gas from gas source and introducing the substantial gases to the generated gases in the inlet tubing to reduce the vacuum generated by the vacuum pump; a monitoring means for monitoring the operating conditions of the hydrogen generating system; and a control means in communication with the monitoring means and adapted to control the operation of

the hydrogen generating system in response to the monitoring means.

The gas source can be atmospheric air, gases from the exhaust gas manifold of the vehicle or gases from the air intake of the vehicle, preferably downstream of the mass air flow sensor. In one embodiment, the supplemental gas is heated over the temperature of ambient air. Alternately or in addition, the supplemental air can be filtered and/or dried.

In one embodiment, the vacuum control arrangement includes a valve for controlling the flow of supplemental gas into the inlet tubing. The supplemental air is preferably introduced to the inlet tubing between a flame arrestor and the vacuum pump.

In another aspect of the present invention, there is provided a hydrogen generating system for use in an internal combustion engine of a vehicle for increasing the efficiency of the engine and decreasing emissions from the engine, the hydrogen generating system comprising: a plurality of modules, each module containing an electrolysis cell for generating hydrogen and oxygen gases by electrolysis of an aqueous solution; a power regulator for providing regulated electrical power to the electrolysis cell, the power regulator generating an AC component; an outlet flow means for introducing the generated gases from the cells into the intake manifold system of the internal combustion engine; a monitoring means for monitoring the operating conditions of the hydrogen generating system; a control means in communication with the monitoring means and adapted to control the operation of the hydrogen generating system in response to the monitoring means; and wherein the AC component of the power regulators are phase locked with a selected module

acting as the master module and a selected others of the modules acting as slave modules.

In one embodiment, each module contains phase locking circuitry, the phase locking circuitry of the master module generating a chopping frequency and inputting the chopping frequency to the slave modules. The system can further comprise a controller selected to prevent the operation of any slave modules not phase locked with the master module. The controller can be a subroutine in the control means.

In another aspect of the present invention there is provided a hydrogen generating system for use in an internal combustion engine of a vehicle for increasing the efficiency of the engine and decreasing emissions from the engine, the hydrogen generating system comprising: an plurality of electrolysis cells for generating hydrogen and oxygen gases by electrolysis of an aqueous solution, the electrolysis cells being electrically connected in series; a power source for providing electrical power to the electrolysis cells through an output circuit; an outlet flow means for introducing the generated gases into the intake manifold system of the internal combustion engine; a monitoring means for monitoring the operating conditions of the hydrogen generating system, the monitoring means including sensor for monitoring the integrity of the output circuit from the power source; and a control means in communication with the monitoring means and adapted to control the operation of the hydrogen generating system in response to the monitoring means, the control means including means in communication with the sensor for controlling operation of the hydrogen generating system based on the integrity of the output circuit.

In one embodiment, the sensor monitors the voltage in the electrical connection between the penultimate and last cells. In another embodiment, the sensor monitors current in the output circuit.

BRIEF DESCRIPTION OF THE DRAWINGS

Preferred embodiments of the present invention are illustrated in the attached drawings in which:

Figure 1 is a perspective view of a preferred embodiment of the hydrogen generating system of the present invention;

Figure 2 is a diagram of a circuit useful for determining battery voltage;

Figures 3A and 3B are diagrams showing cell circuit monitoring arrangements useful in the present invention;

Figure 4 is a perspective, partially cut away view of an electrolysis cell useful in the present invention with an electrolyte level monitoring apparatus shown, in part, schematically;

Figure 5 is a schematic view of an electrolyte level monitoring apparatus according to one aspect of the present invention;

Figure 6 is a schematic view of a gas generator box useful in the present invention;

Figure 7 is a diagram of a phase locking arrangement for a hydrogen generating system according to one aspect of the present invention; and

Figure 8 is a diagram of an intelligent controller useful in the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

A preferred embodiment of a hydrogen generating system of the present invention is illustrated in Figure 1. The hydrogen generating system includes one or more electrolysis cells 10 which are used to generate hydrogen and oxygen gases by electrolysis of a suitable aqueous medium. In the embodiment illustrated in Figure 1, four electrolysis cells 10 are utilized, however other numbers of cells are possible. The number of cells 10 utilized in the system depends upon the capacity of the cell for generating hydrogen and the requirements of the engine to which the system is attached. Thus for passenger cars and light duty trucks utilizing gasoline engines, about four cells with a total capacity of about 500 - 750 cm³ of hydrogen per minute could be utilized. For heavy duty trucks and other heavy equipment, especially those utilizing diesel engines, four, six or eight cells having a total capacity of about 1000 - 1500 cm³ of hydrogen per minute are preferred.

The gases generated by the electrolysis cells 10, as energized by a power source such as battery 11, are fed through a moisture collector 12 which is connected to cells 10 by a suitable tubing 14. Tubing 14 is provided with a check valve 15 that prevents back flow of fluids. The output of the moisture collector 12 is connected to a flame arrestor 18 by means of a suitable tubing 20. Flame arrestor 18 acts to take the energy

out of a flame which could migrate up from the engine. From flame arrestor 18 the gases flow through tubing 24 to an automatic safety shut-off collector 26 which has a ball float valve 27 and a valve seat 28. Collector 26 is selected to shut off the flow of gas, and thereby, the entire system, as will be described hereinafter, if excess amounts of liquid are passed from the electrolysis cell. The flow of gas through the collector 26 will be stopped if the liquid level in the shut-off collector 26 rises such that ball 27 seats in valve seat 28.

The output of the shut-off collector 26 is connected through tubing 30 to a low flow vacuum pump 32 which pumps the gases through tubing 34 to a suitable part of the intake system of the engine. Preferably the flow of gases is regulated. This can be done by adjusting power to the pump or by adjusting the flow by permitting the pump to draw additional fluid to supplement the draw of gas from the electrolysis cells, as will be described hereinafter. The gases may be injected by the pump 32 into the intake system of the engine before the carburetor or injector by connecting the tubing 34 between the outlet of the pump 32 and the air breather box of the intake system of the engine upstream from the air filter. Alternatively, the gases may be injected directly to the carburetor or other fuel delivery system of the engine or may be injected to the intake manifold after the carburetor or fuel delivery system if a proper filtering system is provided.

Pump 32 renders electrolysis cells 10 and the gas delivery system upstream of the pump under vacuum. The vacuum can sometimes be undesirably high, reaching 20 inches of mercury. This causes excessive evaporation of electrolyte and condensation in the gas delivery lines and components and can lead to the formation of ice plugs in the delivery system. To avoid this problem, the vacuum in the line should be maintained at less than

5 inches of mercury and preferably about 2 to 3 inches of mercury. Since it is difficult to achieve this low level vacuum with most commercially available pumps and pumps that can withstand the rigors of automotive applications, a vacuum control system is provided around pump 32, the vacuum control system draws fluid from a source other than the gases generated in the electrolysis cells to supplement gas draw to the pump. The vacuum control permits the vacuum to be maintained at desirable levels by introducing supplemental fluid into the system. The vacuum control system includes a fluid supply tube 35 that conveys a flow of gas from a gas source other than the electrolysis cells to mix with the gases being drawn from the electrolysis cells 10 by the pump. While the gas source can be, for example, the gas in tubing 34 or atmospheric air, preferably the gas source is filtered, heated and/or dried such as gases from the exhaust gas manifold, exhaust gas recirculation systems of the vehicle in which the hydrogen generating system is installed or air from the air intake which has already been metered by the mass air flow sensor. Using air from the air intake permits the monitoring of total air mixing with fuel.

Tube 35 opens into the gas delivery system between flame arrestor 18 and pump 32. A particulate filter 37 is preferably used in the tubing. For safety, tube 35 should not be connected upstream of the flame arrestor, as will be appreciated. To control the flow of air through tube and into the gas delivery system, a needle valve 36 is mounted in tube 35. Needle valve 36 provides precise control over the flow through tube 35 and, thereby, control over and reduction of the vacuum in the gas delivery system. Introduction of supplemental gases can reduce relative humidity in the gas delivery system and reduces electrolyte evaporation by reducing vacuum in the cells. The use of a heated, dried gas source also avoids the formation of ice in the gas delivery system.

Needle valve 36 can be controlled manually or automatically by a control system working with a vacuum sensor. The needle valve can be replaced by other flow control means. For example, in another embodiment, needle valve 36 is replaced by a check valve. The check valve is selected to open, allowing a controlled amount of supplemental gas to flow into the electrolysis gas delivery system, when the gases in the delivery system reach a preselected upper limit of vacuum such as 5 inches of mercury.

The hydrogen generating system includes a power regulator 40 for conditioning power to the electrolysis cells. Preferably power regulator 40 is a controllable, logic-ready device, having as its main component a DC-DC power converter working in current limit with a logic interface capable of output proportional to a binary input. Since the amount of power supplied to the electrolysis cells controls the electrolysis reaction, power regulator 40 is preferably capable of varying the current output to a profile supplied by a controller, which will result in optimum hydrogen and oxygen quantities being produced and then delivered to the engine. This allows the output of the system to be adjusted to optimum profiles, according to the demand.

The electrical lines of the hydrogen generating system can sometimes generate electromagnetic interference (EMI). The EMI can interfere with audio signals such as those in the FM and CB range. To reduce interference, the magnetic field can be reflected back to the emitting components by use of a ferrite bead and capacitor combination 41 or RF shielded coatings around the wires.

A bus arrangement can be used in the electrical system, as this provides flexibility.

A dash module 42 is provided to allow the user to interact with the hydrogen generating system. Dash module 42 is mounted on the motor vehicle in a location easily accessible by the operator of the motor vehicle. The dash module allows the operator of the motor vehicle to control and monitor the hydrogen generating system as required or desired. The dash module 42 is connected via an electrical line 43a to the ignition of the motor vehicle with a suitably sized fuse 44 such as a 5 amp fuse and through lines 43b to other components of the hydrogen generating system.

The hydrogen generating system preferably also provides for visual feedback to the operator of the motor vehicle. The dash module 42 can be provided with one or more LED displays 45a, for example one LED display indicating when the power is turned on to the system, and a second LED display to indicate trouble with the system. Preferably, the system is provided with a display module that includes an alphanumeric display 45b, which can display system messages provided by a controller such as, for example, "System OK", etc.

The hydrogen generating system of the present invention includes suitable control and monitoring means for safe and effective operation. In a preferred embodiment, the control means maximizes system efficiency under various conditions of operation of the engine.

This control can be provided in various ways such as by decentralized or centralized controllers using discrete or intelligent logic. Of course the use of centralized, intelligent control, such as that described hereinafter in reference to Figure 8, is preferred as it is less expensive, more easily adapted to changes in the system, etc. In one embodiment, the monitoring means are in communication with a main microprocessor controller that uses intelligence, established in software, for control of the hydrogen generating system. The central

controller could be located anywhere in the vehicle such as, for example, with the power regulator or in the dash module. Other specialized microcontrollers could be added to communicate with the main microprocessor, if desired.

In the embodiment illustrated in Figure 1, control is decentralized and includes discrete components. While some control is at the sensor level, dash module 42 houses most of the control logic. Various monitoring means and switches, as will be described hereinbelow, communicate with the dash module control logic for system operation.

A first relay or solenoid 46 is operated by dash module 42 to cut power to the power regulator 40 in response to a signal from one or more of the various monitoring means or switches. Another relay 47 is controlled in the same way as relay 46 to work in redundancy therewith. In a preferred embodiment the relays 46 and/or 47 are incorporated into power regulator 40.

When relays 46 and/or 47 shut down the operation of the electrolysis cells, it is preferred that the residual energy stored in the cells 10 be removed. This is preferably accomplished by a relay 66 with a capacitor 68 and resistor 70. When power is cut to the electrolysis cells, relay 66 is activated and connects the cells to ground to bleed off any residual energy stored in the cells.

The controller in dash module 42 also communicates with pump 32 and can shut down its operation in response to signals from the various monitoring means and switches.

For safety and for system protection, one or more safety shutoff switches and safety monitoring features are provided for manual or automatic shutdown and/or adjustment of electrolysis in the system. Not all of the switches/sensors need be in any one

system and, as will be appreciated, some of the monitoring means and switches are best suited to control by an intelligent controller rather than by discrete control.

One switch is indicated in Figure 1 as switch 48 on dash module 42. This switch is actuated by the user to shut power to the system.

The hood of the compartment in which electrolysis cells 10 is positioned is provided with a shutoff switch 49 mounted such that opening the hood of the engine compartment will cause the switch to open and shutdown the hydrogen generating system. The compartment can be for example, the engine compartment, trunk compartment or another compartment on the vehicle body. More than one hood-actuated switch can be used, if desired.

In addition, preferably cells 10 are installed in their own gas generator box 50 (Figure 4) and a safety switch 51 is positioned on the door of the box. Opening the door actuates switch 51, through the control logic of dash module 42, to shut down the hydrogen generating system.

A pressure switch 52 senses the vacuum in line 14. If the vacuum is lost or changes significantly, the sensor communicates a signal to the control logic to shut down the system. Vacuum changes may occur, for example, where there is an ice plug in the delivery line or where the valve in collector 26 is closed.

In a preferred system using an intelligent controller, operation of vacuum pump 32 can also be monitored, particularly with respect to the electrical power being provided to the pump 32. Should the electric circuit to the pump 32 be interrupted, the controller will cause the system to shut down by cutting the electrical power supplied to electrolysis cells 10. In addition,

should the gas supply line of the gases generated by the electrolysis cell 10 become blocked (i.e. by an ice plug, ball 27 seating in valve 28, etc.) such that the pressure in the line changes significantly, the controller will sense that through the current draw of the pump circuit. In particular, if the controller senses that the current draw of the pump is not within an acceptable range, the controller displays a pump failure message at dash module 42 and cuts the power supplied to the electrolysis cells 10.

In one embodiment, pressure switch 52 can be selected to act as a sensor and can operate in a control loop with pump 32. In such an embodiment, the controller monitors the reading of pressure switch 52 and regulates power supplied to the pump to maintain the pressure the gas delivery line within a selected range.

The hydrogen generating system of the present invention also includes a means of determining that the engine is running so that if power is applied to power regulator 40 but the engine is not actually running or the alternator is not properly operating, no electrolysis will take place. This is important to prevent the battery from being run down and to prevent a build up of hydrogen gas. The means to determine that the engine is running could be a sensor monitoring one or more of the engine conditions indicative of engine operation. For example, sensors could be used to monitor one or more of engine vacuum, engine oil pressure, alternator or battery voltage, or signals from the vehicles on-board engine computer. While only one sensor is needed, it may be useful for ease of installation to include inputs for more than one sensor to accommodate more than one type of installation. With the exception of the collection of signals of the vehicle computer, all of these sensors can communicate with a discrete or an intelligent controller.

In the illustrated embodiment, for internal combustion engines, engine operation is determined by a relay⁴~~5~~4 that senses alternator 55 voltage. Relay⁴~~5~~4 is adjusted such that should the alternator voltage drop to a level indicative of alternator inoperation, relay⁴~~5~~4 will interact with relays 46 and 47 to cut power to power regulator 40, thereby shutting down the hydrogen generating system.

In some engines it is difficult to access alternators or to install vacuum or oil pressure switches. However, in most vehicles the battery is accessible. Normally, in a vehicle having an internal combustion engine, when the engine and/or alternator are not functioning, the battery voltage is less than 13V. However, when the engine is operating and the alternator is operating properly, the battery voltage is generally between 13.5 to 13.8V. Thus, a useful circuit for controlling the function of the hydrogen generating system based on engine operation, monitors battery voltage and compares it to a voltage indicative of proper engine/alternator operation. This circuit is advantageously controlled by an intelligent controller.

With reference to Figure 2, one battery voltage monitoring circuit is disclosed. In the circuit, a controller 58 senses battery voltage and compares it to a reference indicative of normal engine operation wherein the alternator is working. If it is determined that the battery voltage is below that indicative of normal engine operation, controller 58 can signal the hydrogen generating system power regulator, as indicated by arrow 57, to cut the power applied to the cells. In addition to shutting the hydrogen generating system down, controller 58 can create a signal which notifies the vehicle user that a power supply problem exists. Using an intelligent controller controller 58 can be checked periodically for battery voltage such that the system can be restarted if the battery voltage recovers. .

One parameter that is preferably monitored and used to control operation of the hydrogen generating system is the level of electrolyte solution in the electrolysis cells 10. In the illustrated embodiment, the electrolysis cells 10 are preferably provided with a level sensor 59, which provides feedback to the control logic of dash module 42 on the level of electrolyte solution in the electrolysis cell 10. If the level of the electrolyte solution in the electrolysis cell 10 drops to a level which would cause excessive exposure of the electrodes, the cell could be damaged or production of gases could become inefficient. In this situation, dash module 42 will shutdown operation of the hydrogen generating system. Some embodiments of electrolyte level monitoring devices are shown in Figures 4 and 5, described hereinafter. If the level of the electrolyte is below a specified limit, then the controller could shut down the system. Alternately, a warning could be displayed to advise the operator to add fluid, preferably steam distilled water, to the cell 10. If the fluid is not added and the level is not brought up above the limit within a set period of time, the controller would shut the system down and indicate the system failure.

To provide an indication of time, an hour meter can be connected into the system. The hour meter can be connected anywhere to monitor the operating time of the cells, but is usually mounted close to the controller. In a preferred embodiment, a micro-controller real time clock is used. The real time clock generates total engine operation time for the vehicle and total operation time for the hydrogen generating system. By software, these sums are stored in non-volatile memory. Thus, hour meters that increase the cost and the size of the controller, for example the dash module, can be eliminated.

Proper generation of gases also relies on the cell circuit condition. In one embodiment, the system includes an arrangement

for monitoring the integrity of the output circuit from the regulator. The arrangement can sense a cell circuit current or voltage. Referring to Figures 3A and 3B, power regulator 40 provides power to electrolysis cells 10, which are connected in series. A break in the circuit such as by boiling dry, connections loosing contact, etc. can be detected by monitoring voltage (Figure 3A) or current (Figure 3B) in the circuit. The useful values or ranges for current or voltage in the system can be determined based on system design.

Referring particularly to Figure 3A, a voltage sensor 60 can monitor voltage between the last two cells of the circuit. To monitor the voltage, one useful arrangement includes a transistor or comparator 61 that operates as a switch. When voltage is sensed in the circuit, an LED 62 on, for example, the dash module is illuminated. When no voltage is sensed, transistor 61 switches the circuit so that LED 62 does not illuminate. Of course, various modifications can be made to this circuit with a similar result. For example, LED 62 can be replaced with an automatic control that can shut down system operation or the transistor can be replaced with an intelligent system.

Of course, the voltage sensing arrangement of Figure 3A will not sense an open circuit in the last cell of the series or in the connection to ground. Thus, alternatively, a current sensing arrangement can be used to determine if the cells are being powered. A current sensing device 64, such as a Hall effect sensor, is positioned anywhere along the circuit, as indicated in phantom. A sensed current outside of a desirable range or a no-current condition signal because of a break anywhere along the circuit is passed to the controller for communication to the user, for example, through the dash module. This can be done easily via software.

Monitoring the temperature of power regulator 40 is sometimes also useful. In particular, if the power regulator heats up beyond acceptable temperatures, the feed back components such as shunts therein can give false readings or, in extreme situations, contacts in the power regulator can be damaged and destroyed, such that the power regulator burns out. Thus, another sensor useful in the present invention is a temperature transducer on the circuit board of the power regulator. The controller can monitor the power regulator temperature, as indicated by the temperature transducer, and control output to the power regulator to maintain the temperature within an acceptable range. Alternatively or in addition, the controller can use temperature information to correct signals from the feed back components.

Many electrolysis cell types are useful in the present invention. Referring to Figure 4, in one embodiment the electrolysis cell 10 utilized in the hydrogen generating system of the present invention is similar to the cell described in detail in U.S. Application No. 09/719,976, also known as WO/00/00671 published January 6, 2000 the disclosure of which is hereby incorporated by reference. Electrolysis cell 10 preferably has a cylindrical shaped case 72 constructed of a suitable material that is inert to the electrolyte solution and not affected by the voltages or temperatures encountered in the electrolysis cell 10. Case 72 should also preferably have a coefficient of expansion that does not cause significant expansion of the dimensions of the cell 10 under the operating conditions of the hydrogen generating system. Preferably, case 72 of the electrolysis cell 10 is a polyvinyl chloride.

The electrolysis cell 10 is provided with a cap 74 that is welded to the sidewall once the components of the electrolysis cell have been assembled. The cap 74 is provided with an outlet 75 to which the tubing 14 is connected. Cell 10 also has a fill plug 76 which is removable to allow the addition of distilled water or electrolyte solution to the cell through a fill port 77. Preferably, the fill plug 76 also incorporates a pressure release mechanism to provide for relief of the pressure within the cell 10 should the interior pressure increase beyond a set limit.

A mesh layer 78 fills an upper area of the cell. Gases produced by the cell pass through mesh 78 to outlet 75 and, in so doing, are dewatered by the mesh. Fill port 77 extends down through the mesh layer so that, during filling, electrolyte does not saturate the mesh.

The electrolysis cell 10 is provided with an electrode assembly 79, which is described in detail in U.S. Application No. 09/719,976. The electrodes that make up the electrode assembly are provided as a monocell, monopolar assembly of an anode and a cathode. The outside cathode and anode electrode plates are provided with adapters 80 for electrical connection to terminals 70.

The materials from which the electrode assembly is constructed are selected to minimize the effects of different coefficients of expansion of the materials, withstand strong corrosive action of the electrolyte solution and provide effective and efficient electrolysis process. Thus, preferably, the electrode plates are a suitable stainless steel material, most preferably nickel plated stainless steel.

The electrolyte solution utilized within the electrolysis cell 10 is preferably a basic aqueous solution to provide for increased efficiency of the electrolysis reaction. Preferably, the solution is also adjusted to remain in solution form and not freeze at extremely low temperatures, down to -40° or more. Most preferably, the electrolyte solution is a 20 to 30% KOH solution.

Figure 4 illustrates one electrolyte level monitoring sensor useful in the present invention. The level monitoring sensor includes a rigid tube 82 installed through an opening in the upper cap 74. Tube 82 is held in position by a bolt 85 threaded down on a threaded portion of the tube. Tube 82 has mounted thereon an upper stop 86 and a lower stop 87. Slidably mounted therebetween is a float 88. Float 88 is selected to float on the electrolyte solution to be used in the cell and is free to ride up and down tube 82 between stops 86 and 87. Sufficient clearance must be provided between tube 82 and float 88 such that the float does not catch on the tube and does not get jammed even in the presence of granular debris which may accumulate in electrolyte solution, over time. Tube 82 houses a circuit, as indicated by conductor 89, connected to a low level indicator such as an LED on dash module 42. The circuit is switched depending on the position of float 88. In particular, one or two reed switches 89a, 89b (shown in phantom as they are positioned in tube 82) are positioned within tube 82. If one reed switch is used it is positioned within the tube adjacent the lower allowable liquid level and if a second reed switch is used it is positioned above the first switch adjacent the upper desirable liquid level. The reed switches are selected to be actuated by a magnet positioned within float 88. The exact positions of the reed switches within tube 82 should be determined with consideration as to the position of magnet within the float, the depth that floats sinks into the surface of the electrolyte (i.e. the density of the float material relative to the electrolyte)

and the desired upper and lower levels of the electrolyte within the cell. When the lower reed switch is activated, it indicates that the cell must be filled. When the cell is being filled, the float will be moved up the tube by the rising liquid level until it is close enough to the reed switch 89a to actuate the switch to indicate that the upper level has been reached and, thereby, to warn the user to stop filling, for example, by illumination of an LED near the cell. This level sensor is improved over many previous sensors since it provides a positive indication of low and high levels. In addition, since it is installed through an opening in case 72 above the level of the electrolyte, it reduces the chances of electrolyte leakage.

Whenever an opening is made through the case or cap of the cell, there is a chance of leakage of electrolyte or gases. Thus, an electrolyte level monitoring sensor, as shown Figure 5, which does not require penetration into the cell is particularly useful. The sensor includes a circuit including an electrical wire 90 wrapped at least one turn about cell 10 adjacent a selected upper or lower level of the electrolyte within the cell. Wire 90 functions as the inductor coil of a tank circuit, which is an inductor and capacitor C connected in parallel. To monitor the level of electrolyte, interface circuitry 92 excites the circuit such that a sine wave is generated and observes evidence of energy loss in the circuit. This information is communicated to the controller for control of the system and to alert the user. When electrolyte such as KOH is present in the tank and reaches the level of the wire the losses in the wire are augmented by energy losses in the electrolyte. Increases in losses in the coil by the electrolyte are significant, for example 50% of the losses of the original coil (i.e. the wire itself). The frequency of the sine wave that should be used is based on absorption to the electrolyte and should not be in the broadcast band for radios or able to create interference with

vehicle systems. Using concentrated KOH as the electrolyte, a frequency of about 2 MHz has shown to be particularly useful.

A number of circuits are useful for setting up an electrolyte level tank circuit sensor. In one embodiment, interface circuitry 92 excites wire 90 with a constant sine wave current. The energy loss by electrolyte results in a reduced sine wave voltage in the tank circuit as detected by the interface circuitry. In another embodiment, a sine wave or pulse is generated by the interface circuitry and used to excite wire 92. When the excitation is stopped, the interface circuitry monitors decay. The presence of electrolyte in the cell at the level of the wire shortens the decay time. In a preferred embodiment, interface circuitry 92 includes an oscillator. Using the oscillator, a sine wave is generated in the circuit itself by feedback. Using a class C oscillator, because of its high efficiency, the power supplied to the oscillator is a direct measurement of the total loss in the tank circuit. When electrolyte, such as KOH, is adjacent the wire, the loss increases accordingly.

One or more tank circuit electrolyte level sensors or one or more reed switches described above can be used in an automatic filler control loop. This innovation eliminates the need for the user to add water as regularly, and allows for a much larger amount to be added at less frequent intervals. It also demands much less care and protects the cells from overfilling. It is possible to use waste heat generated during electrolysis or from the vehicle engine itself in a heat exchanger adjacent a distilled water storage tank, to melt enough distilled water in cold weather to fill the cells.

When using a single sensor of either the reed switch or tank circuit type in a automatic fill control loop, to sense a low

level condition, a valve will open or start at a selected signal from sensor 74 and keep the valve open until a selected amount of water has passed into the cell. An overshoot in the system will overfill the cell slightly, but by a controlled amount. This overshoot will allow the valve/pump to operate infrequently.

When using two sensors, the control loop will operate the valve/pump when the level reaches the lower reed switch or a wire of a first tank circuit. The filling operation continues until the electrolyte level reaches the upper reed switch or upper wire of a second tank circuit.

It is preferred for ease of installation and increased safety that the hydrogen generating system of the present invention be provided as a modular apparatus, as illustrated in Figure 6. In this preferred embodiment, the system includes a gas generator box 50, as noted previously, which contains the electrolysis cells 10, the power regulator 40, and sensor 52 to monitor operation of the electrolysis process. The controller is in dash module 42 (Figure 1). A pump module, and a block of sensors mounted on the vehicle/chassis are provided as separate modules. Box 50 is provided with a closable and lockable door with safety switch 51.

Preferably, box 50 includes an electrolyte level indicator 93 for guidance during refilling the cells. In addition, an interface port (not shown) for establishing communication between the system controller and a diagnostic computer can be provided.

By adopting a modular structure for the hydrogen generating system, installation of the system is simplified as the gas generator may be easily installed and connected to the other components. Box 50 can be quite rugged, formed of steel, thereby shielding the electrolysis cells from potential damage in the event that the vehicle is involved in an accident. The use of the

gas generator box also allows for ease in varying the number of electrolysis cells to match the requirements specific to every individual application. The size and total number of cells installed in the gas generator box defines maximum capacity of hydrogen/oxygen rates. For smaller engines one box may be sufficient, while larger engines may demand a multitude of such boxes connected in series, allowing operation at lower current values.

Where a modular installation is used in a vehicle more than one box is used and each box contains electrolysis cells and a power regulator for those cells. In this arrangement, the AC component of the power regulators in the various boxes can create alias frequencies that become audible in radios. Referring to Figure 7, to overcome this problem, the power regulators can be phase locked together in a master slave configuration. As an example, if three box units 50a, 50b and 50c are used, each will have a power regulator 40a, 40b, 40c. One of the units, for example 50a, can be selected as the master unit. Unit 50a has phase locking circuitry 96 in communication with its power regulator. Master phase locking circuitry 96 selects the total system frequency because there is no frequency input to it. The problem of alias frequencies is handled by master unit 50a inputting a chopping frequency, as indicated at 97, to phase locking circuitry 98 in communication with the power regulators of each of the other units 50b, 50c, termed the slave units. Using the phase locking circuitry 98, the AC components of the power regulators in the slave units 50b, 50c run at the same frequency as that of the master unit 50a. The phase locking circuitry can be injection-locking circuitry in each unit, a combination of phase lock loop chips in each slave unit and a compatible oscillator of any kind in the master unit or circuitry to supply the pulse width modulator in each of the slave units 50b, 50c with a chopping frequency from the master unit 50a.

Alternately, or as a back up to the master-slave phase locking arrangement of Figure 7, the controller can include an interrupt driven subroutine 99 that prevents operation of the hydrogen generating system in any condition giving audio frequencies. If one or more of the cells in the above-noted situation according to Figure 7 were generating an audio frequency, the controller would shut down one or all of the slave units 50b, 50c, leaving only the master unit 50a and any units in-phase with master unit 50a operating. This would eliminate the audio interference.

As discussed with respect to Figure 1, the controller useful in the present hydrogen generating system can include discrete logic or be an intelligent system driven via software. While most of the monitoring routines and control routines described hereinbefore can be provided in discrete logic, it is particularly useful, cost effective and flexible to use an intelligent controller.

Many later model motor vehicles utilize on-board computers (ECU) to control various parameters of the operation of the engine of the motor vehicle particularly with respect to controlling exhaust gas pollution. For example, many vehicles are provided with emission control units to determine the makeup of the exhaust gases or the fuel/air mixture being introduced into the engine. A preferred intelligent controller for the hydrogen generating system is capable of interfacing with the on-board computer to control electrolysis in response to engine conditions.

A particularly useful intelligent controller is shown in Figure 8 and includes a chip including processor 100, volatile

RAM memory 102 and non-volatile, PROM memory 104. The controller also includes external RAM and ROM 106 (i.e. not directly on the processor chip) and a power module 108. To provide for interface to external components, input/output (I/O) ports 110 are provided on the processor chip and interfaces 112 communicate between a plurality of external ports 114 and I/O ports 110 of the chip.

Power module 108 receives raw DC current from the vehicle power source such as the battery and converts and conditions the power for driving the controller.

The interfaces provide communication between the sensors and the controller. The interfaces may include A/D converters to convert analog signals to digital signals, a multiplexer to expand the number of channels that can be monitored etc. External ports 114 provide for: serial digital inputs such as, for example, from the vehicle's on-board computer; parallel digital inputs from, for example, on/off devices such as relays or reed switches; and parallel analog inputs from for example battery voltage sensors, pressure sensors, temperature sensors and pump current sensors. Outputs from external ports 114 include: parallel digital outputs such as to relays and to the power regulator; and serial digital outputs such as to the dash module, engine computer and to ports for communication to diagnostic computers. Interface with the vehicle's on-board computer allows the controller to read the engine's operating parameters (rpm's, speed, mass air flow, throttle position, etc.) and read and, preferably, write into the engine's computer (injector's pulse width, valve timing, ignition timing, etc.).

The PROM stores the software subroutines for the controller. The controller reads all the information from sensors, on-board computer etc. and defines the output profile for the power

regulator and pump, adjusting for optimal efficiency, communicating unsafe conditions or directing system shutdown. The intelligent controller can be programmed to monitor and control the various system devices, to communicate with the engine computer and to interface with the user. As will be appreciated, operation of the controller can be extremely flexible and variable. One example of useful logic for the controller is described in US application 09/628,134, filed July 28, 2000.

In the preferred embodiment, the present invention describes a hydrogen generating system that uses hydrogen and oxygen gases to enhance the properties of the fuel obtaining better combustion efficiency resulting in a cleaner burn and better fuel economy. The reliability of an engine outfitted with such system will increase considerably, resulting in a longer life span, delivering more power and exhausting fewer pollutants. The system is easy to install and complimentary to a gasoline or diesel fueled motor vehicle.

Prototype models of the hydrogen generating system of the present invention were installed on various vehicles including a GMC Suburban, Ford Bronco and Cummins diesel engine for testing purposes. In all cases there was a significant reduction in carbon monoxide emission levels, particularly at engine idle, where the levels decreased up to 95%. Decreases in the level of the carbon monoxide emissions were observed over the full operating range of the engine and carbon monoxide emissions at some of these levels were so low they were not able to be detected. Similarly, hydrocarbon emission levels were also reduced significantly with reductions as high as 90% being observed. The use of the hydrogen generating system of the present invention also resulted in increased performance of the engines with engine torque shown to increase by as much as 10%

and increases of up to 10% in the horse power output of the engine were also observed. Increases in mileage of up to 17% were also observed.

Although various preferred embodiments of the present invention have been described herein in detail, it will be appreciated by those skilled in the art that variations may be made thereto without departing from the spirit of the invention or the scope of the appended claims.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220